



ASAS 18-21 K AS Set 2 x 4 Ah

Compact cordless sabre saw

Compact, low-vibration sabre saw for mobile and universal use for cutting various materials, particularly well suited to hard-to-reach places. Including battery starter set of 2 x 4 Ah ProCORE batteries and rapid charger.

Part number: 7 133 01 62 00 0

FEIN benefits

- > Rapid work progress when sawing thanks to the powerful DC motor.
- > The right solution for virtually all materials and applications: the SDS system for rapid, tool-free saw blade changes.
- > Optimised size and reduced vibrations for low-fatigue working.
- > LED light illuminates the working area.
- > Speed can be variably controlled via throttle.
- > Ergonomic design including soft grip.
- > Compatible with all 18 V AMPShare ProCORE batteries and chargers for even more power and flexibility. Also suitable for 18 V Bosch Professional cordless devices.
- > Maximum work progress with AMPShare 18V ProCORE batteries: COOLPACK 2.0 technology delivers a 135% longer battery life. State-of-the-art cell technology and intelligent battery management deliver 87% more power than with conventional batteries. "Electronic Cell Protection" (ECP) protects the battery from overload, overheating and total discharge.
- > Ideally equipped for every form of use. Mobile working with the L-BOXX system.

Supplied

- ✓ 1 x BIM 130 T18 MS sabre saw blade
- ✓ 1 x BIM 130 T5/8 WP sabre saw blade
- ✓ 1 rapid charger GAL 1880 CV AS
- ✓ 2 x ProCORE 18 V 4.0 Ah AS battery pack
- ✓ 1 tool case (L-Boxx 136)

Technical data

GENERAL TECHNICAL DATA

Battery voltage	18 V
Battery compatibility	Li-ion / ProCORE Li-ion
Battery interface	18 V AMPShare
Strokes	0 - 3 050 rpm
wood	200 mm
Stroke of blade	21 mm
Metal profiles and metal pipes	100 mm
Width	78 mm
Height	177 mm
Length	367 mm
Weight without storage battery	2.00 kg

VIBRATION AND NOISE EMISSION VALUES

Sound pressure level LpA	82 dB
Uncertainty of measured value KpA	5 dB
Sound power level LWA	93 dB
Uncertainty of measured value KWA	5 dB
Vibration value 1 dhv 3-way	8 m/s ²
Uncertainty of measured value Ka	1,5 m/s ²

Examples of use



Powered by



**Kompatibel mit
AMPShare- / Bosch
Professional 18 V**

Akkus. | Compatible
with AMPShare/Bosch

Professional 18 V batteries. | Compatible avec
les batteries 18 V AMPShare/Bosch Professional. |
Compatible con baterías AMPShare/Bosch
Professional de 18 V. | Compatible con le batterie
AMPShare / Bosch Professional da 18 V.